

HA4D FOUR CHANNEL HEADPHONE AMPLIFIER

Description

HEADPHONE AMP FOR PODCAST

For podcast, there are sometimes host and guests recording together in the same room. But if there is only one headphone jack on the interface, you will need a headphone amplifier for all.

INTUITIVE OPERATION

HA4D is a studio-grade quality stereo headphone amplifier. It provides four independent 1/8" headphone output jack. Each headphone output is controlled by the associated level control and mute button for ultra-flexibility adjustment.

Unlike ordinary headphone amp, HA4D is powered by USB-C cable. It is very convenient because it can be powered by power port, power bank or even laptop.

Features

- High quality circuit design. ≥ 100 dB dynamic range. Able to drive headphone to high levels with very low distortion.
- 4 independent headphone outputs with individual volume control and mute button.
- Compact and low-profile design.
- Intuitive operation interface designed for Podcaster.
- Powered by USB-C port.

Included



0.5M length, tip-ring-sleeve interconnection cable, 1/8" (3.5mm) to 1/8" (3.5mm)



Specifications

Gain	24 dB
Clipping Level	+20 dBu
Output impedance	47 Ω
Frequency Response	10 - 50K Hz +/- 1.0 dB
Dynamic Range	≥ 100 dB
S/N Ratio	< 0.03%
Inputs impedance	1,000 Ω
Power	Type-C DC \equiv 5V
Finish	Dark gray
Dimensions	120 \times 70 \times 30mm (4.72" \times 2.75" \times 1.18")
Net Weight	233g (8.21 oz.)

HA4D- Interim Catalogue 暫行目錄

*Specifications are subject to change without notice

*設計和規格如有更改，恕不另行通知