# Superlux

## **E205**


### **STUDIO CONDENSER MICROPHONE**

#### **Description**

Designed for critical home/project/professional studio applications and live performances, this side-address supercardioid studio condenser delivers exceptional detail and low noise. Along with its rugged construction and high-performance specifications, the E205 provides an exceptional level of consistency from model to model.

#### **Features**

- · Large diaphragm for smooth, natural sound and low
- High SPL handling and wide dynamic range provide unmatched versatility
- Supercardioid polar pattern reduces pickup of sounds from the sides and rear, improving isolation of desired sound source



#### Included



Pouch







HM85 pivoting stand mount



Specifications	
Туре	Back Electret Condenser
Polar Pattern	Supercardioid
Frequency Response	30-18,000 Hz
Sensitivity	-38 dBV / Pa ( 12.6 mV )
Output Impedance	200 Ω
Min. Load Impedance	1,000 Ω
S/N Ratio	72 dB
Equivalent Output Noise	< 22 dB SPL
Max. SPL	> 135 dB SPL
Dynamic Range	> 113 dB
Power Requirements	12-52V DC, 3.5 mA
Finish	Black
Connectors	XLR3M
Dimensions	Ø54×150 mm (Ø2.13"×5.9")
Net Weight	400 g (14.1 oz)

#### E205 Frequency Response (Supercardioid)





\*Specifications are subject to change without notice